

Add: Carspa Building, Xinhejia Industrial Zone, Baishi, Yueqing, Wenzhou, Zhejiang, China 325604

Tel: 86-577-61778999, 62767199

Fax: 86-577-62767299

E-mail: info@chinacarspa.com info@carspa.cn

Website: www.carspa.cc

Pure Sine Wave DC to AC Power Inverter - P Series

P4000-4000W with USB Inverter Expert

- Features: ■
- Input & output fully isolated. ◀
 - With USB output port
- **High Surge:** High surge current capability starts difficult loads such as TVS, ◀ camps, motors and other inductive loads.
 - **Soft start:** Smooth start-up of the appliances. ◀
 - Pure Sine Wave Output Waveform: Clean power for sensitive loads. ◀
- **AC output** identical to, and in some cases better than the power supplied by your utility. ◀
 - **Cooling Fan:** Control by load or temperature (optional) ◀
 - **Low Total Harmonic Distortion:** below 3% ◀
 - Remote Control: optional















■ SPECIFICATION:

	MODEL	P4000-121	P4000-241	P4000-122	P4000-242	
OUTPUT	AC VOLTAGE	100/11	0/120VAC	220/	230/240VAC	
	RAT ED POWER	4000W				
	SURGE POWER	8000W(for few seconds)				
	USB	5V, 2. 1A				
	WAVEFORM	Pure Sine Wave(THD<3%)				
	FREQUENCY	50/60Hz ±3Hz				
	AC REGULATION	±5%				
	STANDARD RECEPTACLES	A, B, C, D, E, F, G, H, I, GFCI(optional above)				
	LED INDICATOR	Green for power on, red for failure / protection status indication				
INPUT	NO LOAD CURRENT DRAW	≤1.6A				
	DC VOLTAGE	12V	24V	12V	24V	
	VOLTAGE RANGE	10.5~15.0VDC	21.0-30.0V DC	10.5~15.0VDC	21.0-30.0V DC	
	EFFICIENCY (Typ.)	>87.0%	>90.0%	>87.0%	>90.0%	
	FUSE	30A*16	15A*16	30A*16	15A*16	
	DC CABLE	BVF	R16*6	BVR16*4		
PROTECTION	BAT.LOW ALARM	11±0.5V DC	22±1V DC	11±0.5V DC	22±1V DC	
	BAT.LOW SHUTDOWN	10.5±0.5V DC	21.0±1V DC	10.5±0.5V DC	21.0±1V DC	
	OVERLOAD		Shut	down		
	OVER VOLTAGE	14.8±0.5V DC	29.6±1V DC	14.8±0.5V DC	29.6±1V DC	
	OVER TEMPRETURE	Shut-o	off output voltage, recover autor	matically after temperature g	oes down	
	SHORT CIRCUIT	Shut-off output voltage, repower on to recover				
	BAT.REVERSE POLARITY	By fuse open				
	SOFT START	Yes 5~10s				
	EARTH LEAKAGE		Y	es		
ENVIRONMENT	RESET VOLTAGE AFTER LVS	11.8~12.8V DC	23.6~25.6V DC	11.8~12.8V DC	23.6~25.6V DC	
	WORKING TEMP.	0-40°C				
	WORKING HUMIDITY	20%-90% RH non-condensing				
SAFETY & EMC	STORAGE TEMP.& HUMIDITY	-30°C-70°C 22°F-185°F、10-95%			oft High Turbo Cooling fan	
	EMC	Compliance to EMC Directive 2014/30/EU				
	LVD	Compliance to LVD Directive 2014/35/EU			Universal Protection Battery Low Shadown	
	ROHS	Compliance to EU 2015/863 2011/65/EU				
	EMARK	Compliance to ECE R10.05:2014				
	IEC	Compliance to IEC62368 Compact Design			Compact Design	
OTHERS	DIMENSION	538*23*108mm				
	PACKING	8.98Kg, 2pcs/22.2Kgs/Ctn(5	8.98Kg, 2pcs/22.2Kgs/Ctn(57.5*32*38.5m)			
	COOLING FAN	L.I. I		L.I. I Low Interference Technology		
	APPLICATION	Home and office appliances, Power tools and portable equipments, Vehicle and solar power systemsetc.				
INSTALI	ATION				New Energy Solution	
		SV SOUNA SV SOUNA PURE SINE WAVE AC L	OAD		Mobile AC Source 100% pure sine wave output, better than public power.	